

## For Backflow Testing Applications

Job Name \_\_\_\_\_

Contractor \_\_\_\_\_

Job Location \_\_\_\_\_

Approval \_\_\_\_\_

Engineer \_\_\_\_\_

Contractor's P.O. No. \_\_\_\_\_

Approval \_\_\_\_\_

Representative \_\_\_\_\_

# Series TK-99E

## Backflow Preventer Test Kit

Model TK-99E Backflow Preventer Test Kit is a compact portable device made for testing pressure vacuum breakers, anti-spill vacuum breakers, reduced pressure zone assemblies, and double check valve assemblies. This Backflow Preventer Test Kit has been designed for simplified operation and rugged reliability in a compact package. The TK-99E consists of a gauge with color-coded valves and hoses, hose adapters, shock cord for easy mounting, supply pressure gauge, and a carrying case. Accuracy is +/-1% of full scale.

### Features

- 4½" (114mm) diameter face gauge with dual scale (0-15psi/0-1bar)
- Pressure gauge measuring 0 - 200psi
- Three lightweight needle valves encased in chemical resistant bodies
- Adapters:
  - three ⅜" x ¼" bushings
  - three ½" x ¼" bushings
  - three ¾" x ¼" bushings
  - three ¼" flared fittings
- Hoses: three 6ft (1828mm) hoses with female-threaded swivel couplings
- 16" (41mm) securing strap
- Shock cord
- Replaceable hose filters and valve stem seals
- Durable carrying case

### Pressure-Temperature

Maximum Working Pressure: 200psi (13.7 bar)

Maximum Working Temperature: 200°F (93°C)



G-TB

Watts product specifications in U.S. customary units and metric are approximate and are provided for reference only. For precise measurements, please contact Watts Technical Service. Watts reserves the right to change or modify product design, construction, specifications, or materials without prior notice and without incurring any obligation to make such changes and modifications on Watts products previously or subsequently sold.



**Backflow Prevention Products**

USA: 815 Chestnut St., No. Andover, MA 01845-6098; www.watts.com

Canada: 5435 North Service Rd., Burlington, ONT. L7L 5H7; www.wattscanada.ca

ES-TK-99E 0643

©Watts Regulator Company, 2006